

ALL-IN-ONE BUSINESS INKJET PRINTER

Print | Copy | Scan | Fax

The A3 All-In-One that's ready for business



Key Features:

Full A3 capability for print, copy, scan, fax

Auto 2-sided print

Fast print speeds of up to 22ipm mono and 20 ipm colour

250 sheet paper input | 50 sheet ADF (sort copy up to 30 sheets) | Rear manual feed

6.8cm Touchscreen I CD

Wired and wireless connectivity

Easy to use, productive and robust, the MFC-J3530DW has been engineered to deliver dependable quality, meeting the needs of demanding office environments.

- New build design gives delivers a more robust and easy to operate device suited to a busy work environment
- A new and improved print head increases machine life and ensures exceptional durability

With advanced paper handling the MFC-J3530DW can handle a variety of media types whilst helping you to stay productive with fast prints speeds and a FPOT of just 6 seconds.

- Stay prepared with a 250-sheet capacity paper tray and a rear manual feed slot for printing on a wide range of media
- Enjoy fast and hassle free scanning of multi-paged documents with the 50 sheet Automatic Document Feeder
- · Reduce print costs and paper usage with automatic 2-sided print

Create professional marketing materials and vivid office handouts that won't smudge or fade over time. Keep print costs and frequency of replacements down too with our optional high yield cartridges.

- Show off your sharp black text and vivid colour prints with new pigment based inks
- Save time and money with optional high yield cartridges that deliver yields up to 3,000 mono and 1,500 colour pages**

Connect seamlessly in the office and on the go with Wi-Fi Direct™ for wireless printing from your smartphone, tablet, laptop or desktop, without the need for a router.

- · Stay connected with smartphone, tablet, laptop and desktop compatibility
- · With wireless and Wi-Fi Direct you don't need a router to connect

Capture and digitize paper documents directly from the 6.8cm touchscreen for electronic storage and sharing on the go.

- Scan to popular cloud apps directly from the large 6.8cm intuitive swipe touchscreen
- Capture and convert documents with ease with our exclusive Brother Cloud Apps



General

Technology	Inkjet
LCD Display	6.8cm colour Touchscreen
Memory	128MB
Local Interface	Hi-Speed USB 2.0
Wired Network Interface	10Base-T/100Base-TX
Wireless Network Interface	802.11b/g/n (Infrastructure Mode)
Ink Gauge Indication	Ink levels can easily be displayed on the LCD using the ink management menu

Printer Driver

Macintosh ⁵	OS X v10.9.5/10.10.x/10.11.x CUPS, LPD/LPRng (32 & 64 bit editions)
Windows®	Windows® 10 (32 & 64 bit editions) Windows® 8 (32 & 64 bit editions) Windows® 7 (32 & 64 bit editions) Windows Vista® (32 & 64 bit editions) Windows Vista® (32 & 64 bit editions) Windows® Server 2012, 2012R2 & 2008R2 Windows® Server 2008 (32 & 64 bit editions)

Colour Printer

Speed	22ipm mono & 20ipm colour based on ISO/IEC 24734
Speed (Fast Mode)	Up to 35 pages per minute mono & up to 27 pages per minute colour
Warm-up Time	0 seconds
Resolution	Up to 1200x4800 dpi
2- Sided Print	Yes
Droplet Size	Minimum droplet size of 1.5pl
Colour Enhancement	Brother Image Enhancement allows the user to customise colour output
FPOT (First Print Out Time)	6 seconds

Mobile / Web Based Printing & Scanning

Brother iPrint&Scan	Print from, scan to, send faxes, preview received
	faxes, preview copies and check the machine
(Android)	status from an Android device
Brother iPrint&Scan	Print from, scan to, send faxes, preview received
	faxes, preview copies and check the machine
(iPad / iPhone / iPod)	status from an iPad / iPhone / iPod Touch.
Brother iPrint&Scan	Print from and scan to a smart phone running
(Windows® Phone)	the Windows® Phone Operating System
Brother Print&Scan	Print from and scan to a Windows® 8 or Windows
(Windows® 8 & RT)	RT Tablet
Coople Cloud Drint 2.0	Print most common file types from any Google
Google Cloud Print 2.0	Cloud Print enabled application
AirPrint	Print most common file types from any AirPrint
AllFillit	enabled application
Mopria	Print most common file types from Mopria
- Iviopria	supported Android devices
Brother Print Service	Print from Android devices without a dedicated
Plugin	App
Firement at M6	Print from and scan to Evernote™ without using a
Evernote ^{™6}	PC
Box ⁶	Print from and scan to Box without using a PC
Dropbox ⁶	Print from and scan to Dropbox without using a
Бгорьох	PC
Google Drive™6	Print from and scan to Google Drive™ without
Google Brive	using a PC
OneDrive ⁶	Print from and scan to Microsoft® OneDrive
	without using a PC
Flickr®6	Print from and scan to Flickr® without using a PC
	Print from and scan to Facebook® without using a
Facebook®6	PC
Facebook	PC
	Print from and scan to Evernote™ without using a
Evernote ^{™6}	PC
OneNote ⁶	Scan to Microsoft® OneNote without using a PC
O.I.C.I.O.C.	

Printer Functions

N-up Printing ³	Reduce up to 2, 4, 9, 16 or 25 A4 pages into just one A4 page (Mac, up to 2, 4, 6, 9, or 16)
Poster Printing ⁴	Enlarge 1 A4 page into a poster using 4, 9, 16 or 25 A4 pages
Watermark Printing ⁴	Watermark your documents with predefined text or with your own user-defined messages
Booklet Printing ⁴	Print documents in A5 booklet format using automatic or manual 2-sided print
Print Profiles ³	Store your favourite driver settings as profiles to easily recall them (great for saving time and for less technically adept users)
Print Archive ⁴	An electronic carbon copy feature that saves an electronic copy of all printed documents as a PDF file
Mono Only Mode	If a colour ink runs out, continue printing in Mono

Open Interface

Buether Calutions	Allows the use of 3 rd party solutions & apps,
Brother Solutions	such as PrintSmart Secure Pro to increase
Interface (BSI)	security & productivity

¹Approx declared yield value in accordance with ISO/IEC 24711 ²Calculated with 80g/m² paper ³Windows* & Mac* only ⁴Windows* only

Soptional free download from the Brother Solutions Centre http://solutions.brother.com/ Must be web connected

Trius to ewe Counterceur "Moximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements % It is recommended to use the straight paper output path and the quiet mode feature with paper weights over 105g/m2 % Requires Brother Software

USB Host

Direct Print	Print directly from a USB flash memory drive. The supported file, JPEG,
Direct Scan	Scan directly to a USB flash memory drive. The supported file formats include: PDF, PDF/A, Secure PDF, Signed PDF, JPEG, XPS, TIFF

Scan

Scanner Type	CIS (Contact Image Sensor)
Colour & Mono Scanning	Yes
Scan Speed Mono	A4 11ipm A3 8ipm (images per minute)
2-sided Scan Speed Mono	N/A
Scan Speed Colour	A4 11ipm A3 8ipm (images per minute)
2-sided Scan Speed Colour	N/A
Scan Resolution from ADF	600x600dpi (mono) 300x600dpi (colour)
Scan Resolution from Scanner Glass	1200x2400dpi (mono) 1200x1200dpi (colour)
Interpolated Scan Resolution	Up to 19,200 x 19,200dpi
Colour Depth	16, 777, 216 colour variations (24 bit)
Grey Scale	256 shades of grey (8 bit)
Standard Functions ⁹	Scan to USB, E-mail, OCR, Image & File
Network Scanning	Scan to network folder (Windows® only), FTP, FTP over SSL, Email Server ^{5,} SharePoint ⁹ & Easy Scan to Email ⁶
Cloud Scanning ⁶	Scan direct to Evernote [™] , Box, Dropbox, Google Drive [™] , OneDrive, Picasa, Flickr, Facebook, Evernote [™] , OneNote
Scan Features ⁹	Remove Background, Skip Blank Page, ID Scan, 1 to 2 Scan, Auto Deskew from ADF, Split PDF,
Scan to Microsoft Office ⁶	Scan to Microsoft® Word, Microsoft® Excel & Microsoft® PowerPoint
Scan to Searchable PDF	Scan documents to searchable PDF files
Scan to SharePoint	Scan documents directly into SharePoint
Outline & Scan ⁶	Draw around items to either scan a section or remove a section from the original document
Windows® Web Services Scanning	Scan direct into Windows® (from Windows® 7 & onwards) without needing to install a scanner driver

Scanner Driver

Windows®	TWAIN, WIA Windows® 8 (32 & 64 bit editions), Windows® 7 (32 & 64 bit editions), Windows Vista® (32 & 64 bit editions),
Macintosh ⁵	TWAIN & ICA v10.9.5/10.10.x/10.11.x
Linux ⁵	SANE(32 & 64 bit editions)

Copy

Speed – (A4) Mono/Colour	Up to 12/9cpm (copies per minute)
Automatic 2-Sided Copying	No
FCOT (First Copy Out Time)	6 seconds from ready mode
Resolution	Up to 600 x 600dpi
Multi-Copying / Stack / Sort	Makes up to 99 copies of each page / Stacks or Sorts
Enlargement / Reduction Ratio	Reduce or Increase document sizes from 25% to 400% in 1% increments
N in 1 Copying	Allows the user to compress 2 or 4 pages on to a single A4 sheet
2in1 ID Copying	Allows the user to copy both sides of an ID card to a single A4 sheet
Grey Scale	256 shades of grey (8 bit)
Outline & Copy ⁶	Draw around items to either copy a section or remove a section from the original document
Enlarge Text Copy ⁶	Makes reading copied documents easier if the size of the text on the original document is small

Address Book⁵

Speed Dials	100 x2 locations for numbers and E-mail
	addresses
Group Dial	A combination of up to 6 groups can be stored for
	broadcasting
LDAP	The ability to connect to an external LDAP enabled
	address book, like Microsoft® Exchange

 $\label{eq:Address} \ \text{Address books are only accessible as part of the scan to email server function, available as an}$ optional free download from the Brother Solutions Centre $\underline{\text{http://solutions.brother.com}}$

¹Approx declared yield value in accordance with ISO/IEC 24711 ²Calculated with 80g/m² paper ³Windows* & Mac* only ⁴Windows* only

⁵Optional free download from the Brother Solutions Centre <u>http://solutions.brother.com</u>
⁶Must be web connected

Trius to ewe Counterceur "Moximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements % It is recommended to use the straight paper output path and the quiet mode feature with paper weights over 105g/m2 % Requires Brother Software

Fax

гах	
Fax Modem	33,600bps (Super G3)
Automatic 2-Sided Faxing	Yes
Internet Fax (iFax) ⁵	Fax documents anywhere in the world over the Internet without the use of a telephone line
PC Fax Send ^{10&3}	Send faxes directly from your PC
PC Fax Receive ^{10&4}	Receive faxes directly to your PC
Automatic Redial	Automatic redialling if the recipient fax is busy
Telephone Index	An electronic, alphabetical listing of stored speed dials and group numbers
Distinctive Ring Detection (UK & Denmark only)	An external service that allows two or more telephone numbers shared on a single fixed line and use different ring tones
Speaker / Ring volume	3 levels and off
Fax / Tel Switch	Automatic recognition of fax and telephone reception
Super Fine	Enables quality transmission of very small print and line drawings
Contrast	Auto / light / dark
Enhanced Remote Activate	Transfer a fax call, answered on an extension phone to the fax machine
Delayed Timer	Up to 50
Quick-Scan	Reduce scanning times by scanning a fax into memory before sending. Approximately 2.5 seconds per page A4 standard resolution
Memory Transmission	Up to 200 pages (ITU-T Test Chart, Standard Resolution, JBIG)
Out of Paper Reception	up to 200 pages (ITU-T Test Chart, Standard Resolution, JBIG)
Dual Access	Allows the operator to perform 2 different tasks on the machine at the same time
Broadcasting	Send the same fax message to up to 50 separate locations
Batch Transmission	Stores documents for the same location in the machines memory for transmission in a single call
Auto Reduction	When receiving a single page document longer than A4 (297mm) the fax machine will automatically reduce the message to fit onto a single A4 sheet
ECM (Error Correction Mode)	The MFC will detect line errors during fax transmission and resend the page(s) of the document that had an error (recipient machines must share this feature for it to work)
Fax Forwarding	Sends a fax received in memory to another pre- programmed fax number
Remote Access	Allows users to remotely access their machine
Fax Retrieval	Allows remote access to faxes stored in the machine
Remote Set-up ³	Allows users to set-up the MFC from their PC
Grey Scale	256 shades (8 bit) of grey are available for faxing
Fax Preview	Preview received faxes on the screen

Standard Paper Handling

	Standard Tray – 250 sheets
Paper Input ²	Rear Manual Feed Slot – 1 sheet Multi Purpose Tray –N/A
	Automatic Document Feeder (ADF) – 35 sheets
Paper Output ²	Face up - 100 sheets

Media Specification

Media Types & Weights ⁸	Standardl Tray – Plain, Inkjet, Glossy & Recycled
	paper (between 64 - 220g/m², 260/m² when using
	Brother BP-71 Glossy Paper)
	Manual Feed Slot - Plain, Inkjet, Glossy &
	Recycled paper (between 64 - 220g/m², 260/m² when using Brother BP-71 Glossy Paper)
	Automatic Document Feeder (ADF) – plain &
	recycled paper (between 64 - 90g/m²)
	2-sided Print - plain & recycled paper (between 60
	- 120g/m²)
Envelope Printing	Yes, from the standard tray and manual feed slot:
	Accuracy & reliability will depend on the quality &
	type of envelopes or labels used
	Standard Tray - A3, LGR, LGL, A4, LTR, EXE, Folio,
	A5, A6, Photo(10x15cm), Indexcard(13x20cm),
	Photo-L(9x13cm), Photo-2L(13x18cm), Com-10, DL
	Envelope, Monarch, C5, Mexico Legal, India Legal
	Manual Feed Slot -A3, LGR, LGL, A4, LTR, EXE, Folio, A5, A6, Photo(10x15cm),
	Indexcard(13x20cm), Photo-L(9x13cm), Photo-
	2L(13x18cm), C5, Com-10, DL Envelope, Monarch,
Media Sizes	Mexico Legal, India Legal
	2-sided Print – PC Print: A3, LGR, LGL, Folio, A4, LTR, EXE, A5, Mexico Legal, India Legal
	Copy: A3, LGR, LGL, A4, LTR, A5, Mexico Legal,
	India Legal
	Automatic Document Feeder (ADF) - Width:
	105mm to 297mm x Length: 148mm to 431.8mm
	Scanner Glass
	-Up to Width: 297mm x Length: 431.8mm

Supplies

Supplies	
	Black:
Ink cartridges¹	LC3717BK 550 pages, LC3719XLBK 3,000 pages Cyan:
	LC3717C 550 pages, LC3719XLC 1,500 pages
	Magenta:
	LC3717M 550 pages, LC3719XLM 1,500pages
	Yellow:
	LC-3717Y 550 pages, LC3719XLY 1,500 page
	Ink cartridges , power supply cord, fax line cord,
Carton Contents	driver software for Windows®, Quick Set-Up Guide (PC interface cable NOT included)

The frequency of replacement consumables will vary depending on the complexity of the prints, the percentage of coverage, paper size, and the type of media.

 $^{^{1}\!}Approx$ declared yield value in accordance with ISO/IEC 24711 $^{2}\!Calculated$ with $80g/m^2$ paper

³Windows® & Mac® only ⁴Windows® only

Soptional free download from the Brother Solutions Centre http://solutions.brother.com/ Must be web connected

Mussia we were Commenced.

"Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements

"It is recommended to use the straight paper output path and the quiet mode feature with paper weights over 105g/m2

"Requires Brother Software

Network & Security

Roz.11b/g/n (Infrastructure Mode) t wirelessly without having to go through a less access point (both automatic and manual hods supported) if Protected Setup (WPS) (IP (IPv4 and IPv6) RARP, BOOTP, DHCP, APIPA(Auto IP), S/NetBIOS name resolution, Resolver, mDNS, LLMNR responder, LPR/LPD, om Raw Port/Port9100, IPP, FTPS Client FTP Server, SNMPv1/v2c/v3, TFTP er, P Client, POP3, LDAP, IMAP4, HTTP er P3 & IMAP4 active only when Scan to Email er is downloaded RA, mDNS, NR Responder, DNS Resolver, LPR/LPD, om Raw Port/Port9100, IPP, FTPS Client FTP, SNMPv1/v2c/v3, TFTP server, Services (Print/Scan), SMTP Client, POP3, CIFS to, STPT Client, POP3, LDAP, IMAP4, HTTP er P3 & IMAP4 active only when Scan to Email er is downloaded P*, SMTP-Client, LDAP, IMAP4, ICMPv6, HTTP er P3 & IMAP4 active only when Scan to Email er is downloaded P*, SMTP-AUTH, SSL/TLS (IPPS, HTTPS, FTPS, P, POP3*, IMAP4*), SNMP v3 1x (EAP-MD5, EAP-FAST, PEAP, EAP-TLS, EAP-1), Kerberos len Internet FAX is downloaded.
t wirelessly without having to go through a less access point (both automatic and manual hods supported) if Protected Setup (WPS) /IP (IPv4 and IPv6) RARP, BOOTP, DHCP, APIPA(Auto IP), S/NetBIOS name resolution, Resolver, mDNS, LLMNR responder, LPR/LPD, om Raw Port/Port9100, IPP, /FTPS Client FTP Server, SNMPv1/v2c/v3, TFTP er, P Client, P, Web Services (Print/Scan), Client, SNTP Client, POP3, LDAP, IMAP4, HTTP er P3 & IMAP4 active only when Scan to Email er is downloaded , RA, mDNS, NR Responder, DNS Resolver, LPR/LPD, om Raw Port/Port9100, IPP, /FTPS Client FTP , SNMPv1/v2c/v3 , TFTP server, p. Services (Print/Scan), SMTP Client, POP3, CIFS nt, SNTP Client, LDAP, IMAP4, ICMPv6, HTTP er P3 & IMAP4 active only when Scan to Email er is downloaded P*, SMTP-AUTH, SSL/TLS (IPPS, HTTPS,FTPS, P, POP3*, IMAP4*), SNMP v3 1x (EAP-MD5, EAP-FAST, PEAP, EAP-TLS, EAP-), Kerberos
less access point (both automatic and manual hods supported) ii Protected Setup (WPS) /IP (IPv4 and IPv6) RARP, BOOTP, DHCP, APIPA(Auto IP), S/NetBIOS name resolution, Resolver, mDNS, LLMNR responder, LPR/LPD, om Raw Port/Port9100, IPP, FTPS Client FTP Server, SNMPv1/v2c/v3, TFTP er, P Client, P, Web Services (Print/Scan), Client, SNTP Client, POP3, LDAP, IMAP4, HTTP er P3 & IMAP4 active only when Scan to Email er is downloaded , RA, mDNS, NR Responder, DNS Resolver, LPR/LPD, om Raw Port/Port9100, IPP, FTPS Client FTP , SNMPv1/v2c/v3 , TFTP server, p Services (Print/Scan), SMTP Client, POP3, CIFS nt, SNTP Client, LDAP, IMAP4, ICMPv6, HTTP er p3 & IMAP4 active only when Scan to Email er is downloaded P*, SMTP-AUTH, SSL/TLS (IPPS, HTTPS,FTPS, P, POP3*, IMAP4*), SNMP v3 1x (EAP-MD5, EAP-FAST, PEAP, EAP-TLS, EAP-), Kerberos
/IP (IPv4 and IPv6) . RARP, BOOTP, DHCP, APIPA(Auto IP), . S/NetBIOS name resolution, . Resolver, mDNS, LLMNR responder, LPR/LPD, . om Raw Port/Port9100, IPP, . FTPs Client FTP Server, SNMPv1/v2c/v3, TFTP . Pr, . Pr Client, . Pr Client, . Polient, . Ray mDNS, . Rasponder, . DNS Resolver, . LPR/LPD, . om Raw Port/Port9100, . IPP, . Services (Print/Scan), . SMTP Client, . Polient, . Doervices (Print/Scan), . SMTP Client, . DOP3, . CIFS . LDAP, . IMAP4, . ICMPv6, . HTTP . Polient, . SMTP-AUTH, . SSL/TLS (IPPS, . HTTPS, . Prop3*, . IMAP4*), . SNMP 3 . 1x (EAP-MD5, . EAP-FAST, . PEAP, . EAP-TLS, . EAP), . Kerberos
RARP, BOOTP, DHCP, APIPA(Auto IP), S/NetBIOS name resolution, Resolver, mDNS, LLMNR responder, LPR/LPD, om Raw Port/Port9100, IPP, '[FTPS Client FTP Server, SNMPv1/v2c/v3, TFTP er, P Client, P, Web Services (Print/Scan), Client, SNTP Client, POP3, LDAP, IMAP4, HTTP er P3 & IMAP4 active only when Scan to Email er is downloaded , RA, mDNS, NR Responder, DNS Resolver, LPR/LPD, om Raw Port/Port9100, IPP, FTPS Client FTP , SNMPv1/v2c/v3 , TFTP server, D Services (Print/Scan), SMTP Client, POP3, CIFS nt, SNTP Client, LDAP, IMAP4, ICMPv6, HTTP er P3 & IMAP4 active only when Scan to Email er is downloaded P*, SMTP-AUTH, SSL/TLS (IPPS, HTTPS,FTPS, P, POP3*, IMAP4*), SNMP v3 1x (EAP-MD5, EAP-FAST, PEAP, EAP-TLS, EAP-), Kerberos
S/NetBIOS name resolution, Resolver, mDNS, LLMNR responder, LPR/LPD, om Raw Port/Port9100, IPP, (FTPS Client FTP Server, SNMPv1/v2c/v3, TFTP er, P Client, P, Web Services (Print/Scan), Client, SNTP Client, POP3, LDAP, IMAP4, HTTP er P3 & IMAP4 active only when Scan to Email er is downloaded , RA, mDNS, NR Responder, DNS Resolver, LPR/LPD, om Raw Port/Port9100, IPP, FTPS Client FTP , SNMPv1/v2c/v3 , TFTP server, D Services (Print/Scan), SMTP Client, POP3, CIFS nt, SNTP Client, LDAP, IMAP4, ICMPv6, HTTP er er 13 & IMAP4 active only when Scan to Email er is downloaded P*, SMTP-AUTH, SSL/TLS (IPPS, HTTPS,FTPS, P, POP3*, IMAP4*), SNMP v3 1x (EAP-MD5, EAP-FAST, PEAP, EAP-TLS, EAP-), Kerberos
, RA, mDNS, NR Responder, DNS Resolver, LPR/LPD, om Raw Port/Port9100, IPP, FTPS Client FTP , SNMPv1/v2c/v3 , TFTP server, o Services (Print/Scan), SMTP Client, POP3, CIFS nt, SNTP Client, LDAP, IMAP4, ICMPv6, HTTP er P3 & IMAP4 active only when Scan to Email er is downloaded P*, SMTP-AUTH, SSL/TLS (IPPS, HTTPS,FTPS, P, POP3*, IMAP4*), SNMP v3 1x (EAP-MD5, EAP-FAST, PEAP, EAP-TLS, EAP-), Kerberos
P, POP3*, IMAP4*), SNMP v3 1x (EAP-MD5, EAP-FAST, PEAP, EAP-TLS, EAP-), Kerberos
P*, SMTP-AUTH, SSL/TLS (IPPS, HTTPS,FTPS, P, POP3*, IMAP4*), SNMP v3, 1x (LEAP, EAP-FAST, PEAP, EAP-TLS, EAP-TTLS), seros sen Internet FAX is downloaded.
\™/WPA2™ - Enterprise, Persona), ïi Protected Setup (WPS)
omatically have the device send e-mail alerts n it requires attention, such as when the toner w or needs replacing
eive usage reports on a regular basis via e-mail
rict which network users can or cannot access device over the network (IPv4 only)
rict printing activity to individual or groups of s over a network. Can be used with PC User n Name for up to 10 users

Fleet Management Tools

	Ability to centrally deploy and customise our
Unattended Installer ⁴	drivers and software
	Modular installers that can be distributed through
MSI Installer ⁴	Active Directory®
	Web based print management software
Embedded Web Server	embedded onto the device
BRAdmin Professional 3 ^{4&5}	LAN/WAN management software
Driver Deployment Wizard	Easily create print drivers for hassle free deployment over your network

Environment

Energy Star	Yes
Ink Save Mode	Yes
Sound Power Level	6.38B(A)
Sound Pressure Level	50dB(A) (approx.)
Power Consumption	Operating - 27W Ready - 6W Sleep - 1.6W Off - 0.04W

Dimensions & Weight

With Carton (WxDxH)	681 x 568 x 430mm 23.9KG
Without Carton (WxDxH)	575 x 477 x 305mm 19.6KG

Duty Cycles

Maximum Monthly ⁷ Up to 30,000 pages, monthly print volume	

 $^{^4}$ Approx declared yield value in accordance with ISO/IEC 24711 2 Calculated with 80g/m² paper 3 Windows * & Mac* only 4 Windows * only

^{**}Windows* only
**Optional free download from the Brother Solutions Centre http://solutions.brother.com
**Optional free download from the Brother Solutions Centre http://solutions.brother.com
**Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements
**Bit is recommended to use the straight paper output path and the quiet mode feature with paper weights over 105g/m2
Requires Brother Software

Poordic Swan certification is applicable in Nordic countries only