

Reliable Prints in High Volume

Brilliant Colours, Compact Size





DCP-T536DW







bottles and easy fill ink tanks that lower your colour printing costs. Whether in your home office, living room, or working from the kitchen, enjoy effortless connectivity and quick hassle-free printing.

Memory	128MB
Display	1-Line LCD (16 characters)
Machine Color	White
COLOUR PRINT FUNC	TION
Print Speed (ESAT) ⁽ⁱ⁾	Up to 16.0 ipm (mono) and 9.0 ipm (colou
Print Speed (Eco Mode)	Up to 27.0 ppm (mono) and 11.0 ppm (color
First Print Out Time ⁽ⁱⁱ⁾ (FPOT)	Up to 6.2 sec (mono) and 9.6 sec (colour
Print Resolution	Up to 1,200 x 6,000 dpi (Windows) / Up to 1,200 x 3,600 dpi (Mac)
2-Sided Print	Automatic (Up to A4/LTR)
Borderless Printing	Yes
COLOUR PRINT FUNC	TION
Maximum Copy Size	Up to A4/LTR
Copy Speed (ESAT/sESAT)	Up to 11.0 ipm (mono) and 3.5 ipm (colour) ⁽
Copy Speed (FCOT) ^(iv)	Up to 13.0 sec (mono) and 28.5 sec (colour)
Copy Resolution	1,200 x 1,800 dpi
Enlargement / Reduction Ratio	25% - 400% in 1% increments
N in 1 Copy	2-in-1 / 2-in-1 (ID) / 4-in-1
COLOUR SCAN FUNCT	TION
Maximum Scan Size	Up to A4/LTR
Scan Resolution	Optical: Up to 1,200 x 2,400 dpi Interpolated: Up to 19,200 x 19,200 dpi
Scan Speed (@ 100 dpi)	From scanner FB: 3.35 sec / 4.38 sec (mono/color)
"Scan To" Feature	Image, OCR, Email, File
CONNECTIVITY/NETW	ORKING
Interface	High Speed USB 2.0,WiFi-Direct, Wireless Lan (2.4 GHz)
Mobile Solutions	Brother Mobile Connect App (for Android/iOS/Harmony OS), AirPrint (for iOS), Mopria, Brother Print Service Plugin (for Android
Desktop Solutions	iPrint&Scan Desktop App
Email Print	Yes

Paper Input (Standard Tray)	Up to 150-sheets (80 g/m2)	
Paper Input (Manual Feed Slot)	1 Sheet	
Paper Output	Up to 50-sheets (up to A4)	
Paper Handling Sizes (Standard Tray)	A4, LTR, LGL, Folio, EXE, A5, A6, Photo(102x152mm/4x6"), Indexcard(127x203mm/5x8"), Photo-2L(127x178mm/5x7"), C5 Envelope, Com-10, DL Envelope, Monarch, Photo-L(89x127mm/3.5x5"), Mexico Legal, India Legal	
Paper Handling Sizes (Manual Feed Slot)	A4, LTR, LGL, Folio, EXE, A5, A6, Photo(102x152mm/4x6"), Indexcard(127x203mm/5x8"), Photo-2L(127x178mm/5x7"), C5 Envelope, Com-10, DL Envelope, Monarch, Photo-L(89x127mm/3.5x5")	
Media Type (Standard Tray)	Plain, Inkjet, Glossy (cast/resin), Recycled [Media weight 64-220g/m2]	
Media Type (Manual Feed Slot)	Plain, Inkjet, Glossy (cast/resin), Recycled [Media weight 64-300g/m2]	
SUPPORTED OS AND SOFTWARE		
Supported Operating Systems ^(v)	Windows: 10 / 11 / Server 2016 / 2019 / 2022, macOS ^(vi) v12/13/14/15, Linux OS, Chrome OS	
SUPPLIES		
Ink Bottle ^(vii)	BTD100 BK: Approximate Yield 7,500 A4 pages BTD100 C/M/Y: Approximate Yield 5,000 A4 pages	
Bundled Ink Included	BK: BTD100x1 C/M/Y: BTD100x1	
DIMENSIONS [WIDTH X DEPTH X HEIGHT (WEIGHT)]		
Without Carton	390mm x 343mm x 148.5mm (7.2kg)	
OTHERS		
Machine Life*	30,000 pages or 5 years	
Based on ISO/IEC 24734. For more information, please refer to www.brother.com/rd/printspeed.		

- Based on ISO/ICE 17629. For more information, please refer to www.brother.com./rd/printspeed.
- Based on ISO/IEC 29183 for models without Automatic Document Feeder. For more information, please refer to www.brother.com/rd/printspeed.
- Based on ISO/IEC 24735 Annex D.
- Postage of Individual Carlos and Postage Carlos and Postage Carlos and Postage Carlos and Postage Carlos and PNG file format only. MacOS driver is not provided.

 Postage Carlos PDF/JPG/BMP and PNG file format only. MacOS driver is not provided.

 Approximate page yield is extrapolated based on Brother original Methodology using Test Patterns ISO/IEC 24712.

Machine life is based on either page count or year tallied, whichever comes first and is based on printer usage under following conditions. Printer setting: Default settings for all, Media type: Plain paper, Print pattern: ISO/IEC 24712, Environment: Normal temperature and humidity. Measurements are taken based on Brother's internal testing environment. Data for waste ink pad is based on measurement with assumed monthly usage of 50 to 1,000 pages. To maintain product's quality, the waste ink pad needs to be replaced before reaching page count or year limit depending on the environment and printer models.